

# HL-1210W

**brother**  
at your side

# Compact and Reliable




## Compact and Reliable Monochrome Laser Printer

This affordable, wireless monochrome laser printer is fast, compact and offers excellent print quality. Easy to use, with low running costs, the HL-1210W deals reliably with your daily print requirements.


- Fast printing at up to 20 pages per minute (A4) and less than 10 seconds until the first page is printed
- Compact, space saving design
- Affordable and easy to replace consumables
- Print from mobile devices (iPrint&Scan)

# HL-1210W

With low-priced hardware and genuine consumables, the Brother HL-1210W Wireless Monochrome Laser Printer offers approximately 1,000 prints without compromising on quality. Unlike most printers, the Brother HL-1210W features a separate toner cartridge and drum unit. This means you only need to replace one component at a time, giving you significant cost savings.



Unique rubber material prevents dust from sticking onto the rollers. Dual roller system improves paper feeding by picking one sheet at a time.



A short paper path enables smooth printing and prevents paper from getting stuck.

Description	
Technology	Electrophotographic
CPU Speed	ARM9 200MHz
Standard Memory	32MB
Printer	
Print Speed	Up to 20 ppm
Printer Resolution	600 x 600 dpi, HQ1200 (2400 x 600 dpi) quality
First Print Out Time	Less than 10 secs from ready mode Less than 28 secs from sleep mode Less than 18 secs from sleep mode
Warm Up Time	Less than 23 secs from power on
Emulation	GDI
Control Panel	
LED Display	Orange x1 (Error), Green x1 (Ready), WLAN x1
Control Panel Switches	Power On/Off, Wi-Fi
Connectivity	
Interface	Full-Speed USB2.0, IEEE 802.11b/g/n Wireless
Wireless Mode	IEEE 802.11b/g/n (Infrastructure Mode/Adhoc mode)
Wireless Setup Support Utility	Wi-Fi Protected Setup™ (WPS), AirStation OneTouch Secure System™ (AOSS)
Network Protocols IPV4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMP, Web Services (Print)
Network Protocols IPV6	NDP, RA, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/ Port 9100, IPP, FTP Server, SNMPv1/v2c, HTTP Server, TFTP Client and Server, SMTP Client, ICMPv6, Web Services (Print)
Security	
Wireless Security	WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES)
Wireless Certification	Wi-Fi Certification Mark License (WPA™/WPA2™ - Personal), Wi-Fi Protected Setup (WPS) Identifier Mark License, AOSS
IP-Filter V4	Yes
Networking	
Network Management	Windows:BRAdmin Light, Web Base Management, BRAdmin Professional Mac: BRAdmin Light, Web Base management Linux: Web Base Management
Web Based Management BRAdmin Light	Web browser print server management For setup & small LAN management using Windows or Mac OSX
BRAdmin Professional	For LAN / WAN management using Windows® PC
Email Alerts	E-mail Notification sent to a nominated e-mail address when anything which can disrupt printing activity occurs
Driver Deployment Wizard	A quick & easy way to deploy Brother printer drivers on a networked Windows® PC
Mobile / Web Printing	
iPrintScan	Print JPG & PDF files, web pages and text from the clipboard directly from or scan directly to a smart phone

Software	
Printer Compatibility	Windows 8, 8.1 (32&64bit), Windows 7 (32&64bit), Vista (32&64bit), XP Home Edition, XP Professional (32&64bit), Windows Server 2012 (32&64bit), Windows Server 2012 R2, Windows Server 2008 (32&64bit), Windows Server 2008 R2, Windows Server 2003 (32&64bit) Mac OS X 10.7.5 or greater (Download) Linux Cups/LPR
N-up Printing**	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (MAC OSX, up to 2, 4, 6, 9, or 16)
Poster Printing*	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Manual Duplex	Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)
Header and Footer Printing*	Print the time and date or the user ID on the document
Watermark Printing*	Watermark your documents with predefined text or with your own user-defined messages (Windows Only)
Paper Handling	
Standard Paper Capacity	Up to 150 Sheets
Output Paper Capacity	Up to 50 Sheets Face Down
Media Size Paper Tray	A4, Letter, Legal, Folio, A5, A5(Long Edge), B5, Executive Custom: 148 to 216 mm(W) X 148 to 355.6 mm(L)
Media Types Paper Tray	Plain Paper, Recycled Paper
Media Weights Paper Tray	65-105 gsm
Consumable	
Consumables	Standard Toner Cartridge (TN-1070) Up to 1,000 pages*** Drum (DR-1070) Up to 10,000 pages (1 page per job)
Inbox Consumables	Inbox Toner Cartridge Up to 700 pages*** Drum (DR-1070) Up to 10,000 pages (1 page per job)
Weight and Measures	
Size	340(W) x 238(D) x 189(H)mm
Weight	4 Kg without consumables
Size With Carton	415(W) x 303(D) x 324(H)mm
Weight With Carton	5.5 Kg with consumables
Environment	
Sleep Mode	Yes (1 min, Unchangeable)
Power Save	This enables the printer to consume less energy when not in use
Toner Save	This reduces the toner usage
Power Consumption	Printing:380W or less, Standby:40W or less, Deep Sleep:0.7W or less
Ecology	Power Saving, Toner Saving
TEC Value	700Wh/Week
Noise Level	Sound Pressure: Printing: 51dB, Standby: Inaudible Sound Power: Printing: 6.6B, Standby: Inaudible
Energy Star Compliant	Yes
Temperature	Operating: 10 - 32°C, Storage: 0 - 40°C
Humidity	Operating: 20 - 80%, Storage: 35 - 85% (without condensation)
Others	
Recommended Monthly	
Print Volume	250 to 1,800 pages
Warranty	12 Months Return To Base
Carton Contents	HL-1210W Printer, CD-ROM (including User's Guide), Quick Setup Guide, Inbox Toner Cartridge 700 pages*** Drum (DR-1070) @ 10,000 pages, AC Power Cord

\*Windows Only, \*\*Windows and MacOSX, \*\*\*in accordance with ISO / IEC 19752, \*\*\*\*Downloadable from <http://support.brother.com>

Contact:

**brother**  
at your side



 [facebook.com/brotheraustralia](https://facebook.com/brotheraustralia)  
[www.brother.com.au](http://www.brother.com.au)