



LC-NB-PRO-120

120 W universal multi-range notebook power adapter

The LC-NB-PRO-120 is an universal multi-range notebook power adapter that works with virtually each notebook on the market.

- 120 W
- USB power delivery port
- Multi-range output voltage
- High efficiency up to 89%
- Stabilized output, low ripple & low interference
- Security circuitry:
 - Over-current protection (OCP),
 - Over-load protection (OLP),
 - Over-voltage protection (OVP),
 - Over-temperature protection (OTP),
 - Short-circuit protection (SCP)
- Compatible to many models from e.g.:
 - Acer, Asus, BenQ, Compaq, Dell, Fujitsu, HP,
 - Lenovo, Samsung, Toshiba



Technical specification - LC-NB-PRO-120

Input voltage:	110-240 V
Input frequency:	50/60 Hz
Output power:	120,0 W
Output voltage:	18,5-20,0 V
Output current:	6,00-6,48 A
Standby power:	< 0,5 W
Dimension (product):	170 x 65 x 40 mm
Dimension (retail):	246 x 130 x 50 mm
Weight (product/overall):	0,641 / 0,749 kg
Cable length:	ca. 120 cm
Cable extension:	ca. 150 cm
Material:	plastic
Colour:	black
Mark of conformity:	CE
Barcode:	4260070128882
Manufacturer code:	LC-NB-PRO-120
Included in delivery:	1x notebook power adapter 1x cable extension 10x plug

Nr. No.	Ausgangsspannung Output voltage	Stecker Plug	Kompatibilität Compatibility
USB	5 V / max. 12 W	USB plug	2,40 A max.
J	18,5 V / max. 120 W	4,8 * 1,7 mm	6,48 A max. / Compaq, HP
B	19,0 V / max. 120 W	5,5 * 1,7 mm	6,32 A max. / Acer
L	19,0 V / max. 120 W	5,5 * 2,5 mm	6,32 A max. / Toshiba, Lenovo, Benq, Fujitsu, Dell, Compaq, HP, Asus, Gateway, Averatec
Q	19,5 V / max. 120 W	7,4 * 5,0 mm	6,15 A max. / Dell
U	20,0 V / max. 120 W	11,0 * 4,6 mm	6,00 A max. / Lenovo
Y	19,0 V / max. 120 W	4,0 * 1,7 mm	6,32 A max. / HP
F	19,0 V / max. 120 W	4,0 * 1,35 mm	6,32 A max. / Asus
N	19,0 V / max. 120 W	3,0 * 1,1 mm	6,32 A max. / Samsung
P	19,5 V / max. 120 W	4,5 * 3,0 mm	6,15 A max. / Dell
S	19,0 V / max. 120 W	5,5 * 2,1 mm	6,32 A max. / Asus, Acer